



Connection of your receiver:

1. Unplug your motor
2. Check that your receiver is supplied with a 12V or 24V power supply. If the voltage delivered by the circuit board of your motor is greater (for example, 220V), you will have to install a transformer.
3. Make the following connections with the electrical wires as indicated in the diagram above:
 - Connect channel 1 between terminals 4 and 5 on the receiver (you have to insert the wire in the hole under the screws and then screw them to lock the wire)
 - Connect channel 2 between terminals 6 and 8 on the receiver.
 - If you use the other channels, connect channel 3 between terminals 9 and 10 on the receiver and channel 4 between terminals 11 and 12 on the receiver
 - If the supply power is 24V, connect the terminal + or 24V of the motor to terminal 3 on the receiver. If it is 12V, connect the terminal 12V or + to terminal 2 on the receiver
 - Connect the terminal – or GMD of the motor to terminal 1 on the receiver
4. Your receiver is connected.